

SERIES FED LOW BAND ANTENNAS

A1801-27	
FREQ (MHz)	CUT WHIP
27	52"
28	50"
29	47"
30	44"
31	40"

A1801-30	
FREQ (MHz)	CUT WHIP
30	51"
31	49"
32	46"
33	42"
34	39"
35	37"

A1801-34	
FREQ (MHz)	CUT WHIP
34	52"
35	51"
36	49"
37	47"
38	45"
39	43"
40	39"

A1801-40	
FREQ (MHz)	CUT WHIP
40	52"
41	51"
42	49"
43	48"
44	47"
45	45"
46	44"
47	41"
48	40"

A1801-47	
FREQ (MHz)	CUT WHIP
47	52"
48	51"
49	50"
50	49"
51	47.5"
52	46"
53	44.5"
54	43"

***When cutting a whip that will be used with the standard Comtelco shock spring, the length of the cut whip should be reduced by 2".**